

Telemetry Use Restrictions

Country	Allowed Frequencies (MHz)	Limitations	Region (legacy)	Region (new)
Austria	458.6, 458.65, 458.7, and 458.75		UK	GB
Belgium	458.6, 458.65, 458.7, and 458.75	Yes*	UK	GB
Bulgaria	458.6, 458.65, 458.7, and 458.75	Yes*	UK	GB
Croatia	458.6, 458.65, 458.7, and 458.75		UK	GB
Cyprus	458.6, 458.65, 458.7, and 458.75		UK	GB
Czech Republic	449.8, 449.85, 449.9, 449.95		UK	GB
Denmark	458.6, 458.65, 458.7, and 458.75		UK	GB
Estonia	449.8, 449.85, 449.9, and 449.95	Yes*	ES	ES
Finland	458.6, 458.65, 458.7, and 458.75		UK	GB
France	458.6, 458.65, 458.7, and 458.75		UK	GB
Germany	458.6, 458.65, 458.7, and 458.75		UK	GB
Greece	458.6, 458.65, 458.7, and 458.75		UK	GB
Hungary	433.65 and 433.70	Yes*	SW or SU	CH
Iceland	458.6, 458.65, 458.7, and 458.75		UK	GB
Ireland	458.6, 458.65, 458.7, and 458.75		UK	GB
Italy	458.6, 458.65, 458.7, and 458.75	Yes*	UK	GB
Latvia	449.8, 449.85, 449.9, 449.95	Yes*	UK	GB
Liechtenstein	433.65 and 433.70		SW or SU	CH
Lithuania	449.8, 449.85, 449.9, 449.95	Yes*	UK	GB
Luxembourg	458.6, 458.65, 458.7, and 458.75	Yes*	UK	GB
Malta	458.6, 458.65, 458.7, and 458.75	Yes*	UK	GB
Netherlands	451.03 and 451.09	Yes*	NL	NL
Norway	458.6, 458.65, 458.7, and 458.75		UK	GB
Poland	458.6, 458.65, 458.7, and 458.75		UK	GB
Portugal	458.1125, 458.125, 458.1375, 458.15			PT
Romania	458.6, 458.65, 458.7, and 458.75		UK	GB
Slovak Republic	458.6, 458.65, 458.7, and 458.75		UK	GB
Slovenia	449.8, 449.85, 449.9, 449.95	Yes*	UK	GB
Spain	449.8, 449.85, 449.9, and 449.95		ES	ES
Sweden	458.6, 458.65, 458.7, and 458.75		UK	GB
Switzerland	433.65 and 433.70		SW or SU	CH

* Individual user license required – check with your local authority

Unless otherwise noted, the maximum radiated power output is limited to 100 mW ERP.

Please contact DCI if additional technical information is required.